

REMS Power-Ex-Press Q & E ACC

Electro-hydraulic pipe expander with automatic return

Compact, handy power tool for fast, easy expanding of pipes/rings of the Uponor Quick & Easy system and the Giacomino GX system. For trade and industry. For the building site and the workshop.

Expanding	Ø 16–63 mm Ø ½–2" s ≤ 6.3 mm
-----------	------------------------------------

REMS Power-Ex-Press Q&E ACC – Fast, easy electric expanding up to Ø 63 mm. With automatic return. For Uponor Quick & Easy and Giacomini GX System.

Expander heads

Large expanding capacity up to Ø 63 mm. Automatic, gradual expansion until reaching the given end position which is determined by the expander head. Use of original Uponor Quick & Easy expander heads Ø 16–63 mm, Ø ½–2", manual and hydraulic and Giacomini GX system Ø 16–40 mm, s ≤ 5.5 mm. Expanding device for holding the original Uponor Quick & Easy 54–63 mm, 2" expanding heads. Expanding device for holding the original Uponor Quick & Easy expander heads 16–40 mm, ½–1½" and Giacomini GX system 16–40 mm, s ≤ 5.5 mm as an accessory.

Execution

Compact, robust, job site-proven. Small in size, slender design, drive unit only 5.3 kg. Works anywhere, free-hand, overhead, in confined areas. Ideal weight distribution for single handed operation. Ergonomically designed housing with recessed grip.

Drive

High pressing force for fast, perfect expanding. Powerful electro-mechanical drive with automatic return (ACC), with proven universal motor, 450 W, maintenance-free gear with safety slipping clutch and in-feed system with machine screw spindle. Safety tip switch.



German Quality Product

Tested by electrosuisse >>>

Supply format

REMS Power-Ex-Press Q&E ACC Basic-Pack. Electro-hydraulic pipe expander for expanding tubes/coils of the Uponor Quick & Easy system Ø 16–63 mm, Ø ½–2", s ≤ 6.3 mm. Electro-hydraulic drive with automatic retraction, with proven universal motor 230 V or 110 V, 50–60 Hz, 450 W, robust planetary gear, eccentric reciprocating pump and compact high power hydraulic system. Safety tip switch. Expanding device 54–63 mm, 2". Without expander heads. In a carton.

	Art.-No.
	575017

Note assembly instructions of system supplier. Battery tube expander for other systems on request. Other voltages on request.

Accessories

Description	Art.-No.
Expanding device 16–40 mm, ½–1½" , for holding the original Uponor Quick & Easy expander heads 16–40 mm, ½–1½" and Giacomini GX system 16–40 mm, s ≤ 5.5 mm	575100
Steel case with insert	575278

